

# 54x3W UV LED Par



## International Model

— Dmx control  
7CH (A001Mode)

CH	Function	Description
CH1	Dimmer	Dimmer From Dark to Bright
CH2	Dimmer	UV Dimmer
CH3	Dimmer	UV Dimmer
CH4	Dimmer	UV Dimmer
CH5	Strobe	UV Strobe from Slow to Fast
CH6	Function Optional	0— 50 : CH1-CH5 Control; 51—100: UV Colors; 101—150: UV Color Jump; 151—200: UV Colors Gradual change; 201—250 : UV Colors Pulse Change 251—255 : Sound-activated
CH7	Speed	From Slow to Fast

3CH (d001Mode)

CH	Function	Description
CH1	UV Dimmer	UV Dimmer from Slow to Fast
CH2	UV Dimmer	UV Dimmer from Slow to Fast
CH3	UV Dimmer	UV Dimmer from Slow to Fast



≡ Display Function

NO.	LED	Value	Description
1	d001	001- 512	DMX512 3CH Mode
2	A001	001- 512	DMX512 7CH Mode
3	r255	000 - 255	UV Dimmer from Slow to Fast
4	G255	000 - 255	UV Dimmer from Slow to Fast
5	b255	000 - 255	UV Dimmer from Slow to Fast
6	F000	01 - 99	UV Strobe from Slow to Fast
7	CC15	00 - 15	UV jump from Slow to Fast
8	DE15	00 - 15	UV gradual change from Slow to Fast
9	CP15	00 - 15	UV pulse change from Slow to Fast
10	SOUD	-----	Sound-activated

四、Specifications

Voltage: AC90~240V  
LED: 54pcs 3W UV LED  
CH: DMX Channel  
Control: Dmx512, Master/slave, Auto-run, Sound-activated.